

## RCM 2

## Relay card, 30 V, 1 A

## Technical data

Relay output	NC / NO
Supply voltage	8 - 30 V DC
Current consumption	4.5mA at 8 V, 19 mA at 30 V
Contact rating	30 V, 1 A
Connection	2 x 15cm wire
Dimensions (L x W x H) mm	31 x 12 x 7



RCM 1 is very small universal relay cards that fit most types of security installations (burglar alarm, passage system, fire alarm, etc.). RCM 1 has alternating relay with wire connection for relay control. The out-put terminals are of "push-in" type. When the voltage is applied, the relay is activated and this is indicated by the LED that is switched on.

